

BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
REQNUM	
BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	See Comments
BST TAG PO Field Attr	10 A/N
Description	Requested Number(s) — identifies the telephone number(s) returned
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	See comments
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	The REQNUM is an input parameter only. It is not “returned” by TAG. Rather, across the board in TAG, the input structures populated by the CLEC application prior to a TAG method call are guaranteed to remain unchanged at the time of return from the method; therefore all input values are still available to the CLEC application at the end of a TAG method call.
RES-IW	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Interval::residentialInsideWire
BST TAG PO Field Attr	2 A/N
Description	Residential Inside Wire Interval — Interval for residential unregulated, inside wire, other

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

ROUTE

BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::route
BST TAG PO Field Attr	2 A/N

Description Postal Route — identifies the postal route of the end user's location

BST Firm Order Form	EU
BST Firm Order Field	SATH
BST Firm Order Field Attr	10 A/N
BST CORBA/TAG Order Field	SATH
BST TAG Order Field Attr	10 A/N
BST EDI Firm Order Field	SATH

Comments

SERVICE-INSTRUC-TEXT

BST PO Field Attr	4097 A/N
BST CORBA/TAG PO Response Field	AddressInfoHeader::ServiceInstructionText
BST TAG PO Field Attr	4097 A/N

Description	Service Instructions Text — textual description of special instructions necessary to provide service for the specified address
BST Firm Order Form	EU
BST Firm Order Field	SADLO (see comments)
BST Firm Order Field Attr	100 A/N
BST CORBA/TAG Order Field	lsr::sadlo (see comments)
BST TAG Order Field Attr	100 A/N
BST EDI Firm Order Field	SADLO (see comments)
Comments	SADLO is a concatenation of SERVICE-INSTRUC-TEXT + DRIVE-INSTRUCTIONS + DESC-LOC
STATE	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::state
BST TAG PO Field Attr	2 A/N
Description	Service Address State/Province — identifies the state/province where the service is located
BST Firm Order Form	EU
BST Firm Order Field	EU-STATE
BST Firm Order Field Attr	2A
BST CORBA/TAG Order Field	EULocatonAndAccessHeader::euState
BST TAG Order Field Attr	2A

BST EDI Firm Order Field	STATE-EU
Comments	
STREET-DIR	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::StreetDirectional
BST TAG PO Field Attr	2 A/N
Description	Service Address Street Directional — identifies the street directional of the service address (i.e. “NE”)
BST Firm Order Form	EU
BST Firm Order Field	SASD
BST Firm Order Field Attr	2 A
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sasd
BST TAG Order Field Attr	2 A/N
BST EDI Firm Order Field	SASD
Comments	LENS response name is “Dir-Prefix”
STREET-NAME1	
BST PO Field Attr	44 A/N
BST CORBA/TAG PO Response Field	Address::StreetName
BST TAG PO Field Attr	44 A/N
Description	Service Address Street Name — identifies the street name of the service address (i.e. “Main”)
BST Firm Order Form	EU
BST Firm Order Field	SASN
BST Firm Order Field Attr	50 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sasn

BST TAG Order Field Attr 50 A/N

BST EDI Firm Order Field SASN

Comments

STREET-SUFFIX

BST PO Field Attr 4 A/N

BST CORBA/TAG PO Response Field Address::StreetSuffix

BST TAG PO Field Attr 4 A/N

Description Service Address Street Suffix — identifies the suffix of the street service address (i.e. “NW”)

BST Firm Order Form EU

BST Firm Order Field SASS

BST Firm Order Field Attr 4 A/N

BST CORBA/TAG Order Field EULocationAndAccessHeader::sass

BST TAG Order Field Attr 4 A/N

BST EDI Firm Order Field SASS

Comments

STRUC-BLDG

BST PO Field Attr 14 A/N

BST CORBA/TAG PO Response Field Address::Building

BST TAG PO Field Attr 14 A/N

Description Building — identifies the building located at the street address

BST Firm Order Form EU

BST Firm Order Field EU-BLDG

BST Firm Order Field Attr 9 A/N

BST CORBA/TAG Order Field	EULocationAnldAccess::euBldg
BST TAG Order Field Attr	15A
BST EDI Firm Order Field	BLDG-EU
Comments	
SWITCH-TYPE	
BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	SwitvhInfo::switchType
BST TAG PO Field Attr	4 A/N
Description	Switch Type — identifies the type of switch in which the service is found
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
TARIFF-EFF-DT	
BST PO Field Attr	8 N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::tariffEffectiveDate
BST TAG PO Field Attr	8 N
Description	Tariff Effective Date — identifies the date a feature will become effective in the tariff
BST Firm Order Form	N/A
BST Firm Order Field	N/A

BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	Format CCYYMMDD
TARIFF-EXCHANGE-CODE	
BST PO Field Attr	4 A/N
BST CORBA/TAG PO Response Field	AreaTransferInfo:TraiffExchangeCode
BST TAG PO Field Attr	4 A/N
Description	Tariff Exchange Code — telephone company defined standard abbreviation for a tariff exchange name
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
TARIFF-NOTES	
BST PO Field Attr	65 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::tariffNotes
BST TAG PO Field Attr	65 A/N
Description	Tariff Notes — identifies any tariff notes associated with the service abbreviation
BST Firm Order Form	N/A

Description	Service RestrictionText — text associated with the restriction code, which identifies some limitation of service at a given address
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
TEXT-CODE	
BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	ServiceRestrictionInfo::restrictionCode
BST TAG PO Field Attr	5 A/N
Description	Service Restriction Text Code — ID code for a restriction
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
THOROUGHFARE	
BST PO Field Attr	10 A/N
BST CORBA/TAG PO Response Field	Address::StreetThoroughfare
BST TAG PO Field Attr	10 A/N
Description	Service Address Street Thoroughfare — identifies the thoroughfare portion of the street name of the service (i.e. "Road")
BST Firm Order Form	EU
BST Firm Order Field	SATH
BST Firm Order Field Attr	10 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::sath
BST TAG Order Field Attr	10 A/N
BST EDI Firm Order Field	SATH
Comments	
TN	
BST PO Field Attr	40 A/N
BST CORBA/TAG PO Response Field	TelephoneNumber
BST TAG PO Field Attr	40 A/N
Description	Working Telephone Number(s) — Identifies the working telephone numbers at the end user's location
BST Firm Order Form	<ul style="list-style-type: none"> • RS • PS
BST Firm Order Field	TNS
BST Firm Order Field Attr	17 A/N including 2 preprinted hyphens

BST CORBA/TAG Order Field	RSServiceDetail::tns or PORTService Detail::tns, depending on form
BST TAG Order Field Attr	15 A/N
BST EDI Firm Order Field	TNS
Comments	
TN-OPT-ASCCON	
BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1A/N
Description	TN Option Ascending — identifies if the telephone number(s) returned is ascending
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
TN-OPT-COIN	
BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1 A/N
Description	TN Option Coin — identifies if the telephone number(s) returned is coin
BST Firm Order Form	N/A?

**Pre-Order to Firm Order Mapping Matrix
Pre-Order Response Field**

**CG-MAPP-001
Issue 1A, August, 2001**

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

TN-OPT-IDENT

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1 A/N

Description TN Option Identical — identifies if the telephone number(s) returned is identical

BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A

Comments

TN-OPT-SEQLINE

BST PO Field Attr	1 A/N
BST CORBA/TAG PO Response Field	TNOptions
BST TAG PO Field Attr	1 A/N

Description	TN Option Sequential — identifies if the telephone number(s) returned is sequential
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
TOSOFG	
BST PO Field Attr	8 A/N
BST CORBA/TAG PO Response Field	Carrier Info::serviceOfferingType
BST TAG PO Field Attr	8 A/N
Description	Type of Service Offering — identifies the type of service offered by the carrier
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
UNIT-ROOM	
BST PO Field Attr	15 A/N
BST CORBA/TAG PO Response Field	Address::room

BST TAG PO Field Attr	15 A/N
Description	Room — identifies the room of the end user's location (i.e. "Slip 4" or "Apt 4")
BST Firm Order Form	EU
BST Firm Order Field	EU-ROOM
BST Firm Order Field Attr	Manual: 9 A/N Electronic: 15 A/N
BST CORBA/TAG Order Field	EULocationAndAccess::euRoom
BST TAG Order Field Attr	15A/N
BST EDI Firm Order Field	ROOM-EU
Comments	
USOC	
BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	ProductFeatureInfo::productFeatureUsocList
BST TAG PO Field Attr	5 A/N
Description	Uniform Service Order Code — identifies the USOC associated with the service abbreviation
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	NA/
BST TAG Order Field Attr	N/A

BST EDI Firm Order Field	N/A
Comments	
WATS-SERV-OFF	
BST PO Field Attr	11 A/N
BST CORBA/TAG PO Response Field	SwitchInfo::watsServingOffice
BST TAG PO Field Attr	11 A/N
Description	WATS Serving Office — identifies if the switch is a SATS switch
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A
BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	
XBOUND-STATE	
BST PO Field Attr	2 A/N
BST CORBA/TAG PO Response Field	Address::crossBoundary
BST TAG PO Field Attr	2 A/N
Description	City Cross Boundary State — any situation in which a defined telephone serving area, such as a wire center or community, crosses a defined boundary such as a state line
BST Firm Order Form	N/A
BST Firm Order Field	N/A
BST Firm Order Field Attr	N/A

BST CORBA/TAG Order Field	N/A
BST TAG Order Field Attr	N/A
BST EDI Firm Order Field	N/A
Comments	The data in this field should be the state code (i.e. "GA" for Georgia).
ZIP-CODE	
BST PO Field Attr	5 A/N
BST CORBA/TAG PO Response Field	Address::zipCode
BST TAG PO Field Attr	5 A/N
Description	Service Address Zip Code — identifies the zip code or postal code of the service address
BST Firm Order Form	EU
BST Firm Order Field	EU-ZIP CODE
BST Firm Order Field Attr	Manual: 5 A/N or 10 A/N Electronic: 5 A/N or 9 A/N
BST CORBA/TAG Order Field	EULocationAndAccessHeader::euZipCode
BST TAG Order Field Attr	9A/N
BST EDI Firm Order Field	ZIPCODE-EU
Comments	

A. Scenario's

A.1 Scenario #1 – REQ TYP: M; ACT: C; Description: Change activity on residence port loop service adding block

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT107
N/A	VER	LSR	01
ATN	ATN	LSR	7705550974
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	19991217
DUE DATE	DDD	LSR	19991231
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	C
N/A	CC	LSR	8003
LSO-NPA-TTA	LSO	LSR	770555
N/A	TOS	LSR	2BF
N/A	CIC	LSR	5124
N/A	BAN1	LSR	404Q8480003003
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	JANE DOE
N/A	IMPCON-TEL-NO	LSR	4045557112
N/A	LOCNUM	EU	000
N/A	EU-NAME	EU	MAMA ROSE BELL
HOUSE-NUM	SANO	EU	525

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
STREET-DIR	SASD	EU	N
STREET-NAME1	SASN	EU	MAIN
THOROUGHFARE	SATH	EU	ST
CITY	EU-CITY	EU	ALPH
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	30004
N/A	PQTY	PS	001
N/A	BA	PS	A
N/A	BLOCK	PS	C
N/A	LNA	PS	C
N/A	LNUM	PS	00001
TN	TNS	PS	7705550974

A.2 Scenario #2 – REQ TYP: M; ACT: C; Description: Change activity to port loop business service with phone number change and no transfer of calls

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT65
ATN	ATN	LSR	9125552405
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	19991217
DUE DATE	DDD	LSR	19991221
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	C

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CC	LSR	8002
LSO-NPA-TTA	LSO	LSR	912555
N/A	TOS	LSR	1BF
N/A	CIC	LSR	8002
N/A	BAN1	LSR	706Q8580002002
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	JANE DOE
N/A	IMPCON-TEL-NO	LSR	4045557112
N/A	LOCNUM	EU	000
N/A	EU-NAME	EU	FLOWER SHOP INC
HOUSE-NUM	SANO	EU	304
STREET-NAME1	SASN	EU	PINE
THOROUGHFARE	SATH	EU	AV
CITY	EU-CITY	EU	ALBY
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	31701
N/A	PQTY	PS	001
N/A	LNA	PS	X
N/A	LNUM	PS	00001
N/A	OTN	PS	9125557064
N/A	TC OPT	PS	NO
TN	TNS	PS	9125552405

A.3 Scenario #3 – REQ TYP: M; ACT: C; Description: Change activity on residential port loop service deleting block, changing PIC, and adding PIC freeze

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT71
ATN	ATN	LSR	7705550668
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	19991216
DUE DATE	DDD	LSR	19991230
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	C
N/A	CC	LSR	8002
LSO-NPA-TTA	LSO	LSR	770555
N/A	TOS	LSR	2BF
N/A	CIC	LSR	8002
N/A	BAN1	LSR	770Q895733733
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	JEAN DOE
N/A	IMPCON-TEL-NO	LSR	4045557374
N/A	EU-NAME	EU	JEANIE DREAMER
HOUSE-NUM	SANO	EU	5375
STREET-NAME1	SASN	EU	CHAMBLEE DUNWOODY
THOROUGHFARE	SATH	EU	RD
CITY	EU-CITY	EU	DUN

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	30338
N/A	PQTY	PS	001
N/A	BA	PS	D
N/A	BLOCK	PS	H
N/A	LNA	PS	C
N/A	LNUM	PS	00001
N/A	LPIC	PS	NC
N/A	PIC	PS	0288
TN	TNS	PS	7705550668

A.4 Scenario #4 – REQ TYP: M; ACT: N; Description: New installation of port loop combo residence service with block and working service on premises (WSOP)

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	BST
INQ-NUM	PON	LSR	FT23-A
ATN	ATN	LSR	4045550312
N/A	SC	LSR	LCSC
N/A	D/SENT	LSR	2000114
DUE DATE	DDD	LSR	20000131
N/A	APPTIME-DDD	LSR	0900-1300
N/A	REQ TYP	LSR	MB
N/A	ACT	LSR	N
N/A	CC	LSR	8002

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	PORTTYP	LSR	L
LSO-NPA-TTA	LSO	LSR	404555
N/A	TOS	LSR	1BF
N/A	CIC	LSR	8002
N/A	BAN1	LSR	404Q858002002
N/A	INIT	LSR	JANE DOE
N/A	INIT-TEL-NO	LSR	4045557112
N/A	INIT-FAX-NO	LSR	4045558339
N/A	IMPCON	LSR	LAURA DOE
N/A	IMPCON-TEL-NO	LSR	4045557375
N/A	EU-NAME	EU	DADDY MAX
HOUSE-NUM	SANO	EU	969
STREET-NAME1	SASN	EU	OAK SPRINGS
THOROUGHFARE	SATH	EU	CT
CITY	EU-CITY	EU	ST MT
STATE	EU-STATE	EU	GA
ZIP-CODE	EU-ZIP CODE	EU	30083
N/A	WSOP	EU	V
N/A	PQTY	PS	001
N/A	BA	PS	A
N/A	BLOCK	PS	H
N/A	LNA	PS	N
N/A	LNUM	PS	00001
N/A	LPIC	PS	NONE
N/A	PIC	PS	NONE
TN	TNS	PS	4045550312

- continued -

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	FA	PS	N
N/A	FEATURE	PS	UEG2R
N/A	DLNUM	DL	0001
N/A	LACT	DL	N
N/A	RTY	DL	LML
N/A	LTY	DL	1
N/A	STYC	DL	SL
N/A	TOA	DL	R
N/A	DOI	DL	0
N/A	LTN	DL	4045550312
N/A	LNLN	DL	MAX
N/A	LNFN	DL	DADDY
N/A	LANO	DL	969
N/A	LASN	DL	OAK SPRINGS
N/A	LATH	DL	CT
N/A	LALOC	DL	ST MT
N/A	LAST	DL	GA

A.5 Scenario #5 – REQ TYP: M; ACT: V; Description: Full conversion from multiline resale/retail account to port loop combo service; features are being added and/or deleted

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	CCNA	LSR	ZXL
INQ-NUM	PON	LSR	FT120B
ATN	ATN	LSR	2285559485
N/A	SC	LSR	LCSC

- continued -

BellSouth Pre-Order Field Name	BellSouth Firm Order Field Name	BellSouth Firm Order Form	Example Data
N/A	D/SENT	LSR	19991222
DUE DATE	DDD	LSR	19991230
N/A	REQTYP	LSR	MB
N/A	ACT	LSR	V
N/A	CC	LSR	8002
N/A	PORTTYP	LSR	L
LSO-NPA-TTA	LSO	LSR	228555
N/A	TOS	LSR	1AM
N/A	CIC	LSR	5124
N/A	BAN1	LSR	E
N/A	INIT	LSR	FAY DOE
N/A	INIT-TEL-NO	LSR	2285557498
N/A	INIT-FAX-NO	LSR	2285557449
N/A	IMPCON	LSR	LAURA DOE
N/A	IMPCON-TEL-NO	LSR	2285557375
N/A	EU-NAME	EU	TIE FIGHTER
HOUSE-NUM	SANO	EU	243
STREET-DIR	SASD	EU	E
STREET-NAME1	SASN	EU	2ND
THOROUGHFARE	SATH	EU	ST
CITY	EU-CITY	EU	PASS CHRISTIAN
STATE	EU-STATE	EU	MS
ZIP-CODE	EU-ZIP CODE	EU	39571
N/A	ERL	EU	Y
N/A	EATN	EU	285559458
N/A	PQTY	PS	004

- continued -